

# MyCableMart.com

**Your Home Theatre Connectivity Experts**

6224 Bury Dr, Eden Prairie MN 55346 P. 952-486-8736

## **KEYSTONE JACK INSERT, BLOCK - 3.5MM STEREO AUDIO BLOCK CONNECTOR, WHITE**



**Lengths Available:**

**Colors Available:** White

**Part Numbers this model:** FE-KEY-3MMBL-WH

<b>Sales Category:</b>	Wallplate: Keystone	<b>Wire Gauge (AWG):</b>	26 AWG
<b>Connector A:</b>	3.5mm TRS Stereo Female	<b>Specification:</b>	
<b>Connector B:</b>	3.5mm TRS Stereo Female	<b>Number Ports:</b>	N/A
<b>Export Tariff Code (HST):</b>	8536694030	<b>Transfer Rate:</b>	
<b>Feature / Style:</b>		<b>Images Length/Size Shown:</b>	EA
<b># Positions:</b>		<b>Shielding:</b>	
<b>Convert From/To:</b>		<b>Type:</b>	

This keystone insert features a standard 3.5mm three-conductor female jack which may be used in two or three conductor applications. It is ideal any time a 3.5mm connector is needed at a wall plate. Rear mounted block connector allows simple, fast connection to unterminated Cat5 or CAT3 cable, or any 20-26AWG solid or stranded, UTP or shielded wire. Maximum voltage: 24VAC/DC, 1A. Solid wire is recommended, but stranded wire can be used if properly twisted tightly before insertion. Block will also support a MONO TS type connection simply by not connecting a wire one of the spring blocks

### Specifications and Features

- Remote location of headphone jacks
- Remote microphone connections
- Remote input from PC sound card, MP3 player or iPod
- IR repeater connection
- Accepts 20-26AWG stranded or solder wire
- Remote triggering of A/V components
- Low voltage DC connection
- Wire Legend: R(ight)=Tip, L(eft)=Ring, G(round)=Sleeve, rear of product is labeled RLG. This product is mislabeled, in the United States, Left audio is typically on the Tip and Right audio is on the ring, wire appropriately.
- Color: Bright White

Installation Note: Due to the WIDER (rear) product profile of this product, using MULTIPLE PRODUCTS side-by-side in certain wall-plates is not possible